

## Manual Addendum for URG-SKU



The **URG-SKU** is a video-over-UTP receiver virtually identical to URA-SKU, with the exception that it does not provide audio output and it is designed to connect to **UVx-S** transmitters (such as UV1-S, UV2-S, etc). The receiver is shipped with a universal 5v power supply (required for operation). Please refer to User's Manual UMA1168 for details.

---

### Quick Reference for Video Adjustment

- Press the **SEL** button once to enter the adjustment-mode (without first hitting SEL button the ▲/▼ buttons are inactive).
- All 3 LED's (Red, Green and Blue) on the unit will be turned on.
- The ▲/▼ buttons can now be used to adjust the high frequency (HF) compensation up or down until the video no longer looks smeared.
- Pressing both the ▲/▼ buttons together resets the current adjustment back to zero, so that the user may start over.
- Press the SEL button again to light only one of the 3 RGB LED's. As you press SEL the Red, Green, and Blue LED's will light up one at a time.
- Press the ▲/▼ buttons to move the selected color component to the left and right. Pressing both buttons at the same time resets all skew adjustments and start over if needed.